



PR Series Encased Relays

Description

The PR Series encased relays are designed to control light electrical loads and drive power relays and contactors.

The PR Series features:

- LED relay status indicator
- Color coded wire
- U/L listed

Specifications

Model: PR1110 SPST Relay, Manual Override
Contact Rating: 10 amp
Coil Drive: 10-30 volts AC or DC, also 120 VAC
Current Draw: 35 mA @ 24 VDC; 48 mA @ 24 VA;
37 mA @ 120 VAC
Indication: LED

Specifications

Model: PR1121 SPDT Relay
Contact Rating: 10 amp and up to 1/3 H.P.
Coil Drive: 10-30 volts AC or DC, also 120 VAC
Current Draw: 35 mA @ 24 VDC; 48 mA @ 24 VAC
Indication: LED

Model: PR1122 SPDT Relay
Contact Rating: 10 amp
Coil Drive: 10-30 volts AC or DC, also 208-277 VAC
Current Draw: 35 mA @ 277 VAC
Indication: LED

Model: PR1220 DPDT Relay
Contact Rating: 20 amp and up to 3 H.P.
Coil Drive: 24 volts AC or DC
Current Draw: 50 mA @ 24 VDC; 75 mA @ 24 VAC
Indications: LED

Model: PR2112 One SPST and One SPDT Relay;
Contact Rating: 10 amp Manual Override
Coil Drive: 10-30 volts AC or DC, also 120 VAC
Current Draw: 35 mA @ 24 VDC; 48 mA @ 24 VAC;
37 mA @ 120 VAC
Indication: LED

Model: PR2120 Two SPDT Relays
Contact Rating: 10 amp and up to 1/3 H.P.
Coil Drive: 24 volts AC or DC, also 120 VAC
Current Draw: 35 mA @ 24 VDC; 48 mA @ 24 VAC;
37 mA @ 120 VAC
Indication: LED

Specifications subject to change without notice.


Ordering Information

Part No.	Description
PR1110	One SPST encased relay, manual override, 10-30 volts AC or DC, also 120 VAC
PR1121	One SPDT encased relay, 10-30 volts AC or DC, also 120 VAC
PR1122	One SPDT encased relay, 10-30 volts AC or DC, also 208-277 VAC
PR1220	One DPDT encased relay, 24 volts AC or DC
PR2112	One SPST and one SPDT relay, manual override, 10-30 volts AC or DC, also 120 VAC
PR2120	Two SPDT relays, 24 volts AC or DC, also 120 VAC

Dimensions

Note: inches [mm]

PR1121, PR1122



PR1110, PR1220, PR2112, PR2120

